

ToneBender™ (3-knob) Replica (Tone Burner Modifications Version) Bill of Materials





















Version 2014December03

Copyright 2014 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

Resistors:

Resistor ID	Value	3-band Marking	4-band Marking
R1	1M5 (1.5M)	 brown-green-green	 brown-green-black-yellow
R2	47k	 yellow-violet-orange	 yellow-violet-black-red
R3	220k	 red-red-yellow	 red-red-black-orange
R4	10k	 brown-black-orange	 brown-black-black-red
R5	10k	 brown-black-orange	 brown-black-black-red
R6	3k3 (3.3k)	 orange-orange-red	 orange-orange-black-brown
R7 (Mud Control Potentiometer)	100k Linear		
R8	18k	 brown-gray-orange	 brown-gray-black-red
R9	10k	 brown-black-orange	 brown-black-black-red
R10	None		
R11 (Bass Control Potentiometer)	100k Linear		
R12	10k	 brown-black-orange	 brown-black-black-red
R13 (Volume Control Potentiometer)	100k Log		
R14	None		
R15	None		
R16	220k	 red-red-yellow	 red-red-black-orange
R17	None		





ToneBender™ (3-knob) Replica (Tone Burner Modifications Version) Bill of Materials

Version 2014December03

Copyright 2014 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

R18	1k	 brown-black-red	 brown-black-black-brown
R19	0 ohm or jumper wire	 black	 black
R20 ("String" Control Potentiometer)	1M Linear		
R21(Treble Control Potentiometer)	50k Linear		

Capacitors:

Capacitor ID	Value	Type	Possible Marking
C1	0.1 μ F	Film or Ceramic	104
C2	100pF	Ceramic	101
C3	100 μ F	Aluminum Electrolytic	100 μ F
C4	0.22 μ F	Film or Ceramic	224
C5	10 μ F	Aluminum Electrolytic	10 μ F
C6	0.1 μ F	Film or Ceramic	104
C7	0.015 μ F	Film or Ceramic	153
C8	0.0022 μ F	Film or Ceramic	222
C9	4.7 μ F	Aluminum Electrolytic	4.7 μ F
C10	none		
C11	2.2 μ F	Aluminum Electrolytic	2.2 μ F

Potentiometers:

Part ID	Value	Type
R7 - Mud Control	100k	Linear Taper
R20 – String Control	1M	Linear Taper
R11 - Bass Control	100k	Linear Taper
R21 – Treble Control	50k	Linear Taper
R13 - Volume Control	100k	Log (or Audio) Taper



ToneBender™ (3-knob) Replica (Tone Burner Modifications Version) Bill of Materials

Version 2014December03

Copyright 2014 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

Other:

Part ID	Part Name
D1	1N270 (or other Germanium diode)
D2	LED
Q1	PNP Germanium bipolar junction transistor
Q2	PNP Germanium bipolar junction transistor
Q3	PNP Germanium bipolar junction transistor
J1	Stereo quarter-inch jack
J2	Mono quarter-inch jack
J3	DC Jack
B1	9 volt battery (not included in the Kit)
Sw1	Heavy Duty 3PDT foot switch
Sw2	3-way selector rotary switch
	9v battery snap, Printed Circuit Board, 24 gauge stranded wire, Enclosure, Knobs