

## FTM (fOXX™ Tone Machine™ Replica) Bill of Materials

Version 2012May21

Copyright 2009 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

#### Resistors:

Resistor ID	Value	3-band Marking	4-band Marking
R1	1M5 (1.5M)	brown-green-green	brown-green-black-yellow
R2	47k	yellow-violet-orange	yellow-violet-black-red
R3	1k	brown-black-red	brown-black-black-brown
R4	47k	yellow-violet-orange	yellow-violet-black-red
R5	100k	brown-black-yellow	brown-black-black-orange
R6	100k	brown-black-yellow	brown-black-black-orange
R7	4k7 (4.7k)	yellow-violet-red	yellow-violet-black-browr
R8	4k7 (4.7k)	yellow-violet-red	yellow-violet-black-browr
R9	100k	brown-black-yellow	brown-black-black-orange
R10	100k	brown-black-yellow	brown-black-black-orange
R11 (Sustain Control	50k Linear Potentiometer		
R12	220 ohm	red-red-brown	red-red-black-black
R13	100k	brown-black-yellow	brown-black-black-orang
R14	150k	brown-green-yellow	brown-green-black-orang
R15	15k	brown-green-orange	brown-green-black-red
R16	10k	brown-black-orange	brown-black-black-red



# FTM (fOXX™ Tone Machine™ Replica) Bill of Materials

Version 2012May21

Copyright 2009 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

R17	1k	brown-black-red	brown-black-black-brown
R18	22k	red-red-orange	red-red-black-red
R19	4k7 (4.7k)	yellow-violet-red	yellow-violet-black-brown
R20 (Tone Control)	50k Linear Potentiometer		
R21	470k	yellow-violet-yellow	yellow-violet-black-orange
R22	47k	yellow-violet-orange	yellow-violet-black-red
R23	10k	brown-black-orange	brown-black-black-red
R24	1k5 (1.5k)	brown-green-red	brown-green-black-brown
R25 (Volume Control)	50k Linear Potentiometer		
R26	1k	brown-black-red	brown-black-black-brown

Capacitors:

Capacitor ID	Value	Туре	Possible Marking
C1	0.1ųF	Film or Ceramic	104
C2	0.001ųF	Film or Ceramic	102
C3	0.1ųF	Film or Ceramic	104
C4	10ųF	Aluminum Electrolytic	10ųF
C5	10ųF	Aluminum Electrolytic	10ųF
C6	10ųF	Aluminum Electrolytic	10ųF
C7	10ųF	Aluminum Electrolytic	10ųF
C8	10ųF	Aluminum Electrolytic	10ųF
C9	10ųF	Aluminum Electrolytic	10ųF
C10	0.0033ųF	Film or Ceramic	332



### FTM (fOXX™ Tone Machine™ Replica) Bill of Materials

Version 2012May21

Copyright 2009 JD Sleep

Permission refused for posting/serving this file from any site other than www.generalguitargadgets.com

Trademarks are property of their owners

C11	0.047ųF	Film or Ceramic	473
C12	10ųF	Aluminum Electrolytic	10ųF
C13	10ųF	Aluminum Electrolytic	10ųF

#### **Potentiometers:**

Part ID	Value	Type
R11 - Sustain Control	50k	Linear Taper
R20 - Tone Control	50k	Linear Taper
R25 - Volume	50k	Linear Taper

#### Other:

Part ID	Part Name	
Q1, Q2, Q3, Q4	2N3904 or other NPN Bipolar Transistors	
D1, D2, D3, D4	1N34A Germanium Diodes	
D5	LED	
Sw2	On-off Mini Toggle Switch	
J1	Stereo quarter-inch jack	
J2	Mono quarter-inch jack	
J3	DC Jack	
B1	9 volt battery (not included in the Kit)	
Sw1	Heavy Duty 3PDT foot switch	
	9v battery snap, Printed Circuit Board, 24 gauge stranded wire, Enclosure, Knobs	